



WIRING CONNECTOR

DIP SWITCH ADJUSTMENTS

SOLDER SIDE

PARTS SIDE

A	P1-UP	P1-DOWN	1
B	P1-LEFT	P1-RIGHT	2
C	P1-PUSH 1	P1-PUSH 2	3
D	P2-UP	P2-DOWN	4
E	P2-LEFT	P2-RIGHT	5
F	P2-PUSH 1	P2-PUSH 2	6
H	COIN 1	COIN 2	7
J	GND	GND	8
K	GND	GND	9
L	+5	+5	10
M	+12		11
N		+12	12
P	+5	+5	13
R	GND	GND	14
S	GND	GND	15
T	1 PLAY	2 PLAY	16
U	TEST	SERVICE	17
V	COUNTER 1	COUNTER 2	18
W	SP (+)	SP (-)	19
X		R	20
Y	G	B	21
Z	GND	SYNC	22

SWITCH 1

		1	2	3	4	5	6
Number of Player	3	OFF	OFF				
	4	ON	OFF				
	5	OFF	ON				
	6	ON	ON				
Bonus Player 20000 (1 st) 50000				OFF			
				ON			
(after 2nd) 60000 90000					OFF		
					ON		
Demo Sound	WITH					OFF	
	WITHOUT					ON	
Type	TABLE UP RIGHT						OFF ON

SWITCH 2

		1	2	3	4	5	6
Coin 1	1 Coin 1 Credit	OFF	OFF				
	1 " 2 "	ON	OFF				
	2 " 1 "	OFF	ON				
Coin 2	Free Play	ON	ON				
	1 Coin 3 Credit			OFF	OFF		
	1 " 6 "			ON	OFF		
	2 " 3 "			OFF	ON		
	3 " 1 "			ON	ON		
Difficulty	EASY						OFF
	HARD						ON
Screen Inversion							

