

# JUNGLE KING

CONNECTOR "G"

CONNECTOR "H"

1	GND	10	TV-SYNC
2	+5V	11	SOUND (-)
3	+5V	12	COIN (B)
4	+5V	13	2P SELECT
5	+12V	14	2P UP
6	+12V	15	2P DOWN
7	GND	16	1P-LEFT
8	TV-GND	17	1P-RIGHT
9	TV-S	18	2P JUMP

CONNECTOR "I"

1	GND	10	TV-SYNC
2	+5V	11	SOUND (+)
3	+5V	12	COIN (A)
4	+5V	13	SERVICE
5	+12V	14	1P SELECT
6	+12V	15	1P UP
7	GND	16	1P DOWN
8	TV-R	17	2P-LEFT (SPEED)
9	TV-G	18	2P-RIGHT

\* DIP SW A

SW	1	2	3	4	5	6	7	8
BONDS POINTS	ON	ON	*			*	*	
	OFF	ON	*			*	*	
	ON	OFF	*			*	*	
NO OF MAN	OFF	OFF	*			*	*	
			*	ON	ON	*	*	
TYPE			*	OFF	OFF	*	*	
			*	ON	OFF	*	*	
	TABLE TOP		*	OFF	OFF	*	*	ON
UPRIGHT			*	OFF	OFF	*	*	OFF

\* Always OFF

OFF  
ON

\* DIP SW B

SW	1 WAY			2 WAY				
1 COIN 1 PLAY	ON				ON			
	OFF	ON	ON	ON	OFF	ON	ON	ON
	ON				ON			
	OFF				OFF			OFF
2 COIN 1 PLAY					ON			
					OFF			OFF
3 COIN 1 PLAY					ON			
					OFF			OFF

\* DIP SW C

SW	1	2	3	4	5	6	7	8
FREE PLAY								
							ON	

SOLDER SIDE

1	GND	15	+5V
2	GND	16	+5V
3	GND	17	+5V
4	GND	18	+5V

CONNECTOR "I"

CONNECTOR SIDE